

VERIFICATION OF TRANSLATION


Translation of the certified copy of:

Japanese Patent Application No. 2003-082830

Filed in JAPAN on March 25, 2003

I, Seiko TOKI, of FURUYA INTERNATIONAL PATENT OFFICE of Dai2 Meiho Building, 9th Floor, 19-5, Nishi-Shinjuku 1-Chome, Shinjuku-ku, Tokyo 160-0023 JAPAN, fully conversant with the English and the Japanese languages, hereby certify that to the best of my knowledge and belief the following is a true translation into the English language of the above document, which has been made by me and for which I accept responsibility.

Signed this April 21, 2009

A handwritten signature in black ink, consisting of a large, stylized 'S' followed by a horizontal line and a small 'x' mark.

Seiko Toki

[Document Name] Patent Application

[Reference Number] 0252824

[Date of Filing] March 25, 2003

[Whom to be Forwarded] Director-General of the Patent Office

5 [International Patent Classification] H04B 7/26

H04b 7/02

[Title of Invention] Radio Base Station Apparatus and Base Station Controller

[Number of Claims] 5

[Inventor]

10 [Residence or Domicile] c/o FUJITSU LIMITED, 1-1, Kamikodanaka 4-chome, Nakahara-ku,
Kawasaki-shi, Kanagawa

[Name or Title] Yoshiharu Tajima

[Applicant]

[Identification Number] 000005223

15 [Name or Title] FUJITSU LIMITED

[Agent]

[Identification Number] 100072718

[Patent Attorney]

[Name or Title] Fumio Furuya

20 [Telephone Number] 3343-2901

[Notification of Fee]

[Prepayment Ledger Number] 013354

[Amount of Payment] ¥21,000-

[List of Attached Documents]

25 [Item] Specification 1 Set

[Item] Drawings 1 Set

[Item] Abstract 1 Set

[General Power of Attorney Number] 9704947

[Name of Document] Specification

[Title of Invention] RADIO BASE STATION APPARATUS AND BASE STATION CONTROLLER

[Claims]

[Claim 1] A radio base station apparatus comprising:

5 a receiving section for receiving a signal from a terminal via a radio channel assigned to the terminal;

an identifying section for identifying a particular radio base station which is to maintain the radio channel between the radio base station apparatus and the terminal during a process of a diversity handover for the terminal;

10 a network interface section for delivering the signal to a network when a local station is not the particular radio base station; and

an inter-office interface section for delivering to the network a composite wave of the signal and a signal that is forwarded from a radio base station forming a wireless zone adjacent to a wireless zone formed by the local station, when the local station is the particular
15 radio base station, the forwarded signal having arrived at the radio base station from the terminal via the radio channel.

[Claim 2] A radio base station apparatus comprising:

a receiving section for receiving a signal from a terminal via a radio channel assigned to the terminal;

20 an identifying section for identifying a particular radio base station which is to maintain the radio channel between the radio base station apparatus and the terminal during a process of a diversity handover for the terminal;

a network interface section for delivering the signal to a network when a local station is not the particular radio base station; and

25 an inter-office interface section for forwarding the signal to the particular radio base

station among radio base stations that form wireless zones adjacent to a wireless zone formed by the local station when the local station is not the particular radio base station.

[Claim 3] A radio base station apparatus comprising:

a network interface section for capturing a signal that is delivered from a network in
5 a physical layer of the network;

an identifying section for identifying a particular radio base station which is to maintain a radio channel assigned to a terminal as a receiving end of the signal during a process of a diversity handover for the terminal;

a transmitting section for transmitting the signal to the terminal via the radio
10 channel; and

an inter-office interface section for forwarding the signal to a radio base station forming a wireless zone adjacent to a wireless zone formed by a local station, when the local station is the particular radio base station.

[Claim 4] A radio base station apparatus comprising:

15 an inter-office interface section for capturing a signal whose destination is a terminal and that have been forwarded from a radio base station forming a wireless zone adjacent to a wireless zone formed by a local station;

an identifying section for identifying a particular radio base station which is to maintain a radio channel assigned to the terminal during a process of a diversity handover for
20 the terminal; and

a transmitting section for transmitting the signal to the terminal via the radio channel when the local station is not the particular radio base station.

[Claim 5]

A base station controller comprising:

25 a channel controlling section for performing a channel control over a terminal in

cooperation with a radio base station forming a wireless zone where the terminal can visit;
and

a network interface section for interfacing with a network under the channel control,
the network being a network in which a communication channel is to be formed between said
5 base station controller and the terminal via all or part of the radio base station, wherein

said channel controlling section determines, among the radio base station, a
particular radio base station according to the channel control and all or part of configuration
of the wireless zone, channel allocation, and frequency allocation, the particular radio base
station being to maintain a radio channel assigned to the terminal during a process of a
10 diversity handover for the terminal.

[Detailed description of the invention]

[0001]

[Technical field of the invention]

The present invention relates to a radio base station apparatus that forms a wireless
15 zone in a mobile communication system in which a terminal or a call occurring at a terminal is
given different IP addresses for wireless zones. It also relates a base station controller that
performs a channel control over a terminal visiting a wireless zone.

[0002]

[Prior art]

20 In recent years, data terminals and communication terminals accessible to the
Internet have spread rapidly. For radio transmission channels in next-generation mobile
communication systems, use of the IP (Internet protocol) has been studied, because of its
high compatibility with the Internet, for replacement the multiple access schemes which
comply with the circuit switching system. Also, radio transmission channels and line
25 transmission sections have become seamless step by step.

Fig. 6 shows the configuration of an exemplary mobile communication system in which different IP addresses are assigned for respective wireless zones.

[0003]

As shown in Fig. 6, radio base stations 70-1 and 70-2 form overlapping wireless zones 81-1 and 81-2, respectively. A terminal 82 locates in one of the wireless zones 81-1 and 81-2, for example, in the wireless zone 81-1. The radio base stations 70-1 and 70-2 are connected to a base station controlling station 84 via communication links 83-1 and 83-2, respectively.

[0004]

10 The radio base station 70-1 has the following components:

- Antenna 71-1

- Antenna duplexer 72-1 that is connected to the feeding point of the antenna 71-1.

- Receiving part 73-1 that is connected to the reception output of the antenna duplexer 72-1.

15 - Router 74-1 that is connected to the one end of an inter-office link provided between the radio base station 70-1 and an exchange (not shown), and to whose incoming route the output of the receiving part 73-1 is connected.

- Transmitting part 77-1 that is connected in series to the outgoing route of the router 74-1 and whose output is connected to the transmission input of the antenna duplexer 72-1.

20 - Controlling part 76-1 having input/output ports that are connected to the control terminals of the receiving part 73-1, the router 74-1, and the transmitting part 77-1, respectively, and a communication port that is connected to the one end of the above-mentioned communication link 83-1.

25 The radio base station 70-2 has the same configuration as the radio base station

70-1. Therefore, the components of the radio base station 70-2 will be given the same reference symbols as those of the radio base station 70-1 except that the former will have a suffix "2" instead of a suffix "1," and will not be described or shown in the drawings.

[0005]

5 In the mobile communication system having the above configuration, the radio base stations 70-1 and 70-2 form wireless zones 81-1 and 81-2 that comply with a predetermined multiple access scheme and channel allocation, by cooperating with, via the respective communication links 83-1 and 83-2, the base station controlling station 84 performing a channel control and call setting in cooperation with the above-mentioned
10 exchange.

[0006]

Recognizing that a call that occurred at the terminal 82 has become a complete call during the course of such a channel control, the radio base station 70-1 assigns the terminal 82 a unique IP address (for the sake of simplicity, it is assumed here to be "192.168.0.2" and
15 will be referred to as "first IP address") that is not assigned to any other terminals or calls.

[0007]

When the terminal 82 has moved to the overlap region of the wireless zones 81-1 and 81-2 before the complete call disappears, it issues a handover request to the radio base station 70-1 according to a prescribed channel control procedure (indicated by symbol (a) in
20 Fig. 7).

The radio base station 70-1 receives the handover request at the antenna 71-1, the antenna duplexer 72-1, and the receiving part 73-1 and the controlling part 76-1 thereof forwards it to the base station controlling station 84 via the communication link 83-1 (indicated by symbol (b) in Fig. 7).

25 [0008]

The base station controlling station 84 performs the following processing in response to the handover request:

- Determines a wireless zone (hereinafter referred to as "transition destination wireless zone"; for the sake of simplicity, it is assumed to be the wireless zone 81-2) to which

5 the terminal 82 should make a transition.

- Determines a radio channel (hereinafter referred to as "transition destination radio channel") that can be assigned by the radio base station 70-2 which forms the wireless zone 81-2 and that is not assigned to any terminal or call.

[0009]

10 - Sends, to the radio base station 70-2, via the communication link 83-2, a transmission start request for starting a transmission on the transition destination radio channel (indicated by symbol (c) in Fig. 7).

- Sends, to the radio base station 70-1, via the communication link 83-1, a handover request confirmation that the terminal 82 should make a transition to the above transition

15 destination radio channel (indicated by symbol (d) in Fig. 7).

[0010]

During the above processing, the base station controlling station 84 may cooperate with the radio base station 70-2 in any form.

In the radio base station 70-1, when recognizing the handover request confirmation,

20 the controlling part 76-1 sends the handover request confirmation to the terminal 82 via the transmitting part 77-1, the antenna duplexer 72-1, and the antenna 71-1 (indicated by symbol (e) in Fig. 7).

[0011]

When recognizing the handover request confirmation, the terminal 82 performs the

25 following processing:

- Performs a series of operations (hereinafter referred to simply as "radio channel establishment") including synchronization establishment in the transition destination radio channel and a continuity check by cooperating, when necessary, with the radio base station 70-2 that forms the transition destination zone (indicated by symbol (f) in Fig. 7).

5 [0012]

- When the radio channel establishment has completed normally, sends to the radio base station 70-2 a message called "binding update" which is an assignment request for a second IP address that complies with the transition destination wireless zone and is to replace the above-mentioned first IP address (indicated by symbol (g) in Fig. 7).

10 The radio base station 70-2 sends the binding update message to the base station controlling station 84 via the communication link 83-2.

[0013]

Recognizing the binding update message, the base station controlling station 84 performs the following processing:

15 - Secures an IP address (for the sake of simplicity, it is assumed here to be "192.168.1.2") as a second IP address by itself or in cooperation with the radio base station 70-2. The IP address is in such a value range that the radio base station 70-2 is allottable and is not assigned to any terminal or call (indicated by symbol (i) in Fig. 7). In the following description, for the sake of simplicity, it is assumed that the host address portions of the first
20 IP address and the second IP address are defined under different subnet masks corresponding to the respective radio base stations 70-1 and 70-2 (wireless zones 81-1 and 81-2) so as to secure compatibility with the known mobile-IP that does not conform to the mobile communication and the radio transmission sufficiently.

[0014]

25 - Allows a relationship between the terminal 82 (or the transition destination channel

assigned to the terminal 82) and the second IP address to be reflected in routing information held in the router 74-2 (indicated by symbol (j) in Fig. 7).

- Sends a message "binding update confirmation" containing the second IP address to the terminal 82 via the communication link 83-2 and the radio base station 70-2 (indicated by symbol (k) in Fig. 7).

[0015]

The terminal 82 completes the handover by using, as one of the following, the second IP address contained in the binding update confirmation as an IP address that has been assigned in place of the first IP address (indicated by symbol (m) in Fig. 7):

- Transmission source address that should be placed in the header of each packet that is sent from the local station.

- Address that should be placed in the header of each of packets to be directed to the local station among packets received from the radio base station 70-2 via the transition destination radio channel.

With the above processing, it is able to achieve a handover between the overlapping wireless zones 81-1 and 81-2 formed by the respective radio base stations 70-1 and 70-2 with high reliability, as long as the routers 74-1 and 74-2 of the radio base stations 70-1 and 70-2 are given proper pieces of routing information, and first and second IP addresses comply with those pieces of routing information.

[0016]

[Patent Document 1]

JP-A-2001-45534 (claims 4, 6, 8, and 9, paragraphs 0013, 0015, 0018, 0023, 0034, 0035, 0040-0042, 0044-0046, 0050, 0056-0058, 0060, 0063-0065, and 0067)

[Patent Document 2]

JP-A-2001-189954 (abstract, paragraph 0031)

[Patent Document 3]

JP-A-10-117167 (abstract, claim 1)

[Patent Document 4]

JP-A-11-122672 (claims 1-16)

5 [Patent Document 5]

JP-A-10-190633 (claim 1, paragraph 0001)

[Patent Document 6]

JP-T-10-509287 (abstract)

[Patent Document 7]

10 JP-A-2000-286898 (abstract, claim 1, paragraphs 0003 and 0016)

[0017]

[Problems to be solved by the invention]

Incidentally, in the above prior art examples, a handover is attained by executing the second processing (indicated by symbols (g)-(m) in Fig. 7) for assignment of a second IP
15 address that is to replace a first IP address after completion of the first processing (indicated by symbols (a)-(f) in Fig. 7) for realizing update of a physical radio channel.

That is, during such a handover process, every time the terminal 82 moves to a new wireless zone, it is given a new IP address as appropriate in accordance with a new radio channel that is physically different from an old one.

20 [0018]

Therefore, the prior art examples enable transmission services of a variety of transmission information by using the IP; however, they cannot realize a diversity handover in accordance with substantially varying distances between the relative positions of the terminal 82 and the radio base stations 70-1 and 70-2 and according to the transmitting power
25 control to solve the near-far problem of the CDMA scheme. Also, they cannot take

advantage of merits of the CDMA scheme to maintain high, stable transmission quality of a radio transmission channel.

[0019]

An object of the present invention is to provide a radio base station apparatus and a
5 base station controller that realize a stable and reliable diversity handover without altering the basic configuration thereof to a large extent.

[0020]

[Means to solve the problem]

Fig. 1 is a first principle block diagram of radio base station apparatus according to
10 the invention.

In an invention according to Claim 1, a receiving section 11 receives a signal from a terminal 10 via a radio channel assigned to the terminal 10. An identifying section 12 identifies a particular radio base station that is to maintain the radio channel between the radio base station apparatus and the terminal 10 during a process of a diversity handover for
15 the terminal 10. A network interface section 14 delivers the signal to a network 13 if the local station is not the particular radio base station. An inter-office interface section 16 delivers to the network 13 composite waves of the signal and signals that have arrived at radio base stations 15-1 to 15-N forming wireless zones adjacent to a wireless zone formed by the local station from the terminal 10 via the radio channel and that are forwarded
20 therefrom, if the local station is the particular radio base station.

[0021]

With this configuration, signals arriving in parallel at the radio base station apparatus according to the invention and the radio base stations 15-1 to 15-N from the terminal 10 via the radio channel are combined with each other and delivered to the network 13 in the
25 baseband, intermediate frequency band, or radio frequency band.

Therefore, it is possible to realize a diversity handover for an upstream radio transmission channel formed between the local station and the terminal 10 as long as signals arriving at radio base stations 15-1 to 15-N that form the adjacent wireless zones from the terminal 10 are forwarded in the above-described manner.

5 [0022]

In an invention according to Claim 2, the receiving section 11 receives a signal from a terminal 10 via a radio channel assigned to the terminal 10. The identifying section 12 identifies a particular radio base station that is to maintain the radio channel between the radio base station apparatus and the terminal 10 during a process of a diversity handover for the terminal 10. The network interface section 14A delivers the signal to a network 13 if the local station is not the particular radio base station. The inter-office interface section 16A forwards the signal to the particular radio base station among radio base stations 15-1 to 15-N that form wireless zones adjacent to a wireless zone formed by the local station if the local station is not the particular radio base station.

15 [0023]

With this configuration, a signal arriving at the radio base station apparatus according to the invention from the terminal 10 via the radio channel is delivered to the particular radio base station in the baseband, intermediate frequency band, or radio frequency band, as a signal that is to be combined with a signal arriving directly at the particular radio base station from the terminal 10 in parallel with the above signal and be forwarded to the network 13.

[0024]

This makes it possible to realize a diversity handover for an upstream radio transmission channel formed between the local station and the terminal 10 as long as the signal combining and signal delivery to the network 13 are performed in the particular radio

station.

Fig. 2 is a second principle block diagram of radio base station apparatus according to the invention.

In an invention according to Claim 3, a network interface section 22 captures a signal that is delivered from a network 21 in a physical layer of the network 21. An identifying section 24 identifies a particular radio base station that is to maintain a radio channel assigned to a terminal 23 as a receiving end of the signal during a process of a diversity handover for the terminal 23. A transmitting section 25 transmits the signal to the terminal 23 via the radio channel. An inter-office interface section 27 forwards the signal to radio base stations 26-1 to 26-N that form wireless zones adjacent to a wireless zone formed by the local station if the local station is the particular radio base station.

[0025]

With this configuration, the signal having been delivered from the network 21 in the physical layer and is to be transmitted to the terminal 23 from the local station (i.e., transmitting section 25) is forwarded to the radio base stations 26-1 to 26-N that form the adjacent wireless zones in the baseband, intermediate frequency band, or radio frequency band. Therefore, it is possible realize a diversity handover for a downstream radio transmission channel formed between the local station and the terminal 23 as long as the radio base stations 26-1 to 26-N transmit the above signal to the terminal 23, and the signal is diversity-received at the terminal 23.

[0026]

In an invention according to Claim 4, the inter-office interface section 27A captures a signal whose destination is a terminal 23 and that have been forwarded from radio base stations 26-1 to 26-N that form wireless zones adjacent to a wireless zone formed by the local station. The identifying section 24A identifies a particular radio base station that is to

maintain a radio channel assigned to the terminal 23 as a reception end of the signal during a process of a diversity handover for the terminal 23. The transmitting section 25A transmits the signal to the terminal 23 via the radio channel if the local station is not the particular radio base station.

5 With this configuration, signals delivered from the radio base stations 26-1 to 26-N that form the adjacent wireless zones in the baseband, intermediate frequency band, or radio frequency band are transmitted to the radio channel assigned to the terminal 23.

[0027]

10 This makes it possible to realize a diversity handover for a downstream radio transmission channel formed between the local station and the terminal 23 as long as signals that arrive at the terminal 23 in parallel from the radio base station according to the invention and the radio base stations 26-1 to 26-N that form the adjacent wireless zones are diversity-received at the terminal 23.

[0028]

15 In a more specific concept of the invention according to Claim 1, an inter-office link securing section 31 secures links to be used for transfer of signals between the local station and the radio base stations 15-1 to 15-N according to a procedure of a channel control for assigning the radio channel to the terminal 10 or through cooperation with the base station controller 30 performing the channel control. The inter-office interface section 16
20 combines the signals with signals that are forwarded via the links secured by the inter-office link securing section 31.

[0029]

25 With this configuration, signals are delivered via the links secured by the inter-office link securing section 31 to be combined with a signal arriving at the radio base station apparatus according to the invention from the terminal 10 and delivered to the network 13.

This allows the radio base station apparatus to be adaptable to an increase or a decrease in the number of wireless zones used for a diversity handover for the terminal 10, which changes due to movement of the terminal 10, as well as to reduce the number of links used for delivering the signals.

5 [0030]

In a more specific concept of the invention according to Claim 2, the inter-office link securing section 31 secures links to be used for transfer of the signal between the local station and the radio base stations 15-1 to 15-N according to a procedure of a channel control for assigning the radio channel to the terminal 10 or through cooperation with the
10 base station controller 30 performing the channel control. The inter-office interface section 16A forwards the signal to the particular radio base station via the link secured by the inter-office link securing section 31.

[0031]

With this configuration, signals having arrived at the radio base station apparatus
15 according to the invention from the terminal 10 are delivered to other radio base stations via the links secured by the inter-office link securing section 31.

This allows the radio base station apparatus to be adaptable to an increase or a decrease in the number of wireless zones used for a diversity handover for the terminal 10, which changes due to movement of the terminal 10, as well as to reduce the number of links
20 used for delivering the signals.

[0032]

In a more specific concept of the invention according to Claim 3, an inter-office link securing section 31A secures links to be used for transfer of the signal between the local station and the radio base stations 26-1 to 26-N according to a procedure of a channel
25 control for assigning the radio channel to the terminal 23 or through cooperation with the

base station controller 30A for performing the channel control. The inter-office interface section 17 forwards the signal via the links secured by the inter-office link securing section 31A.

[0033]

5 With this configuration, signals having been delivered from the network 21 in the physical layer of the network 21 are delivered to other radio base stations via the links secured by the inter-office link securing section 31A.

 This allows the radio base station apparatus to be adaptable to an increase or a decrease in the number of wireless zones used for a diversity handover for the terminal 23, 10 which changes due to movement of the terminal 23, as well as to reduce the number of links used for delivering the signals.

[0034]

 In a more specific concept of the invention according to Claim 4, the inter-office link securing section 31A secures links to be used for transfer of the signals between the local 15 station and the radio base stations 26-1 to 26-N according to a procedure of a channel control for assigning the radio channel to the terminal 23 or through cooperation with the base station controller 30A performing the channel control. The inter-office interface section 27A captures signals that are forwarded via the links secured by the inter-office link securing section 31A.

20 [0035]

 With this configuration, the transmitting section 25A transmits signals delivered from other radio base stations to the terminal 23 via the links secured by the inter-office link securing section 31A.

 This allows the radio base station apparatus to be adaptable to an increase or a 25 decrease in the number of wireless zones used for a diversity handover for the terminal 23,

which changes due to movement of the terminal 23, as well as to reduce the number of links used for delivering the signals.

[0036]

Fig. 3 is a principle block diagram of base station controllers according to the
5 invention.

In a more specific concept of the invention according to Claim 5, a channel
controlling section 43 performs a channel control over a terminal 40 by cooperating with
radio base stations 42-1 to 42-P that form wireless zones 41-1 to 41-P where the terminal
40 can visit. A network interface section 45 interfaces with a network 44, under the channel
10 control, where a communication channel is to be formed between the base station controller
and the terminal 40 via all or part of the radio base stations 42-1 to 42-P. The channel
controlling section 43 determines, among the radio base stations 42-1 to 42-P, a particular
radio base station, which is to maintain a radio channel assigned to the terminal 40 during a
process of a diversity handover for the terminal 40, according to the channel control and all or
15 part of configurations of the wireless zones 41-1 to 41-P, channel allocation, and frequency
allocation.

[0037]

With this configuration, a particular radio base station is determined as appropriate
according to all or part of the configurations of the wireless zones 41-1 to 41-P, the channel
20 allocation, and the frequency allocation, and it is not limited to a radio base station that forms
a wireless zone where the terminal 40 for which a diversity handover is performed locates
when a complete call has occurred at the terminal 40 or when the diversity handover is
started.

[0038]

This allows the base radio controller to be adaptable to various configurations of

mobile communication systems, and can optimize the form of a diversity handover.

In a more specific concept of the invention according to Claim 5, the channel controlling section 43 performs the channel control such that a radio base station is to be the particular radio base station, the radio base station is the one to form a wireless zone where
5 the diversity handover is done in a suitable manner for all or part of configuration of a wireless zone, channel allocation, and frequency allocation.

[0039]

Therefore, It is not always the case that the same radio base station continues to be a particular radio base station until a complete call occurring at the terminal 40 for which a
10 diversity handover is performed disappears. It is possible to change the particular radio base station as appropriate to a radio base station that forms a wireless zone where the diversity handover is performed in a suitable form for all or part of the configuration of a wireless zone, the channel allocation, and the frequency allocation.

[0040]

15 This allows the base radio controller to be adaptable to various configurations of mobile communication systems, and can optimize the form of a diversity handover.

[0041]

[Preferred embodiment of the invention]

Embodiments of the present invention will be hereinafter described in detail with
20 reference to the drawings.

Fig. 4 shows first and second embodiments of the invention.

In the embodiments, radio base stations 50-1 and 50-2 are provided in place of the radio base stations 70-1 and 70-2 and a bypass link 51 is provided between the radio base stations 50-1 and 50-2.

25 The radio base station 50-1 is different from the radio base station 70-1 shown in

Fig. 6 in the following points:

[0042]

(1) A receiving part 52-1, a transmitting part 53-1, and a controlling part 54-1 are provided in place of the receiving part 73-1, the transmitting part 75-1, and the controlling part 76-1, respectively.

(2) A link interface section 55-1 is provided which has one end of the bypass link 51 and has the following terminals:

- Control terminal that is connected to a corresponding input/output port of the controlling part 54-1.

- Reception output that is connected to baseband inputs of the receiving part 52-1 and the transmitting part 53-1.

- Transmission input that is connected to a baseband output of the receiving part 52-1.

Fig. 5 illustrates the operations of the first and second embodiments of the invention.

[0043]

The operation of the first embodiment according to the invention will be described below with reference to Figs. 4 and 5.

As in the case of the conventional example, the base station controlling station 84 plays a leading role in performing a channel control relating to the wireless zones 81-1 and 81-2 by cooperating with the radio base stations 50-1 and 50-2 via the communication links 83-1 and 83-2.

In addition to the above channel control, the base station controlling station 84 manages, as resources, in a unified manner, a plurality of channels (hereinafter referred to as "bypass channels") that are formed in the bypass link 51 according to a prescribed multiple access scheme.

[0044]

In the radio base station 50-C, the controlling part 54-C performs the following processing for a radio channel for which the radio base station 50-C does not relate to a diversity handover at all:

- 5 - Instructs the receiving part 52-C and the transmitting part 53-C that they should perform the same processing as in the conventional example.
- Instructs the link interface part 55-C that it need not perform any special processing.

[0045]

- 10 The radio base stations 50-1 and 50-2 form the wireless zones 81-1 and 81-2 that comply with a prescribed multiple access scheme and channel allocation by cooperating with, via the respective communication links 83-1 and 83-2, the base station controlling station 84 that performs a channel control and also performs call setting by cooperating with the above-mentioned exchange.

- 15 When recognizing that a call that occurred at the terminal 82 has become a complete call during the course of such a channel control, the radio base station 50-1 assigns the terminal 82 a unique first IP address that is not assigned to any other terminals or calls.

[0046]

- 20 In the following description, the wireless zone 81-1 where the terminal 82 exists at an instant when the complete call has occurred will be referred to as a particular wireless zone. A radio channel that is assigned to the complete call (i.e., terminal 82) at this time will be referred to as a particular radio channel.

- 25 When the terminal 82 has moved to the overlap region of the wireless zones 81-1 and 81-2 before the complete call disappears, the terminal 82 sends a handover request to that effect to the radio base station 70-1 according to a prescribed channel control procedure

(indicated by symbol (a) in Fig. 5).

[0047]

In the radio base station 50-1 the controlling part 54-1 forwards, to the base station controlling station 84, via the communication link 83-1, the handover request that has been
5 received at the antenna 71-1, the antenna duplexer 72-1, and the receiving part 73-1 (indicated by symbol (b) in Fig. 5).

The base station controlling station 84 performs the following processing in response to the handover request:

– Determines a wireless zone (hereinafter referred to as "joint wireless zone"; for the
10 sake of simplicity, it is assumed to be the wireless zone 81-2) that the terminal 82 should use jointly for the diversity handover.

[0048]

– Determines a radio channel (hereinafter referred to as "joint radio channel") that
can be assigned by the radio base station 50-2 forming the wireless zone 81-2 and that is
15 not assigned to any terminal or call.

– Sends, to the radio base station 50-2, via the communication link 83-2, a
transmission start request that a transmission on the joint radio channel should be started
(indicated by symbol (c) in Fig. 5).

[0049]

– Sends, to the radio base station 50-1, via the communication link 83-1, a handover
20 request confirmation that the terminal 82 can access the downstream link of the joint radio channel (indicated by symbol (d) in Fig. 5).

During the above processing, the base station controlling station 84 may cooperate with the radio base station 70-2 in any form.

[0050]

In the radio base station 50-1, when recognizing the handover request confirmation, the controlling part 54-1 sends the handover request confirmation to the terminal 82 via the transmitting part 77-1, the antenna duplexer 72-1, and the antenna 71-1 (indicated by symbol (e) in Fig. 5).

5 Further, at the time of the sending, the controlling part 54-1 recognizes that for the diversity handover for the terminal 82, the local station is a particular radio base station that should play a leading role in forming and maintaining a radio transmission channel involving the terminal 82.

[0051]

10 On the other hand, in the radio base station 50-2, the controlling part 54-2 recognizes that the local station is not the above-mentioned particular radio base station, in response to the transmission start request.

When recognizing the handover request confirmation, the terminal 82 performs a series of operations (hereinafter referred to simply as "radio channel establishment") including synchronization establishment in the joint radio channel and a continuity check by cooperating, when necessary, with the radio base station 50-2 that forms the joint wireless zone (indicated by symbol (f) in Fig. 5).

[0052]

When the joint radio channel to be used for the diversity handover for the terminal 82 has been secured in this manner, the base station controlling station 84 assigns a free, unique bypass channel (hereinafter referred to simply as "bypass channel") among the above-mentioned plurality of bypass channels for each of pairs of each joint radio channel and the particular radio channel by cooperating with the radio base stations 50-1 and 50-2 (controlling parts 54-1 and 54-2) that form the particular wireless zone and all the joint wireless zones, respectively (for the sake of simplicity, it is assumed that only the wireless

20

25

zone 81-2 exists).

[0053]

In the following description, an item common to the radio base stations 50-1 and 50-2 may be described by using a reference symbol having a suffix "C" which corresponds to
5 either of suffixes "1" and "2."

In the radio base station 50-2, the controlling part 54-2 gives the receiving part 52-2, the transmitting part 53-2, and the link interface part 55-2 binary information indicating that the local station is not the above-mentioned particular radio base station.

[0054]

10 The receiving part 52-2, the transmitting part 53-2, and the link interface part 55-2 perform the following processing in accordance with the logical value of the binary information:

- The receiving part 52-2 generates a baseband signal by despread a reception wave that has arrived from the terminal 82 (indicated by symbol (1) in Fig. 5) and has been
15 supplied via the antenna 71-2 and the antenna duplexer 72-2 and passes the generated baseband signal (hereinafter referred to as "upstream transfer subject signal") to the link interface part 55-2 without performing decision decoding or transmission channel decoding on it.

[0055]

20 - The link interface part 55-2 forwards the upstream transfer subject signal to the radio base station 50-1 via the bypass channel (indicated by symbol (2) in Fig. 5).

On the other hand, in the radio base station 50-1, the controlling part 54-1 gives the receiving part 52-1, the transmitting part 53-1, and the link interface part 55-1 binary information indicating that the local station is the above-mentioned particular radio base
25 station.

[0056]

The receiving part 52-1, the transmitting part 53-1, and the link interface part 55-1 perform the following processing in accordance with the logical value of the binary information:

5 - The link interface part 55-1 passes the above-mentioned upstream transfer subject signal to the receiving part 52-1 (indicated by symbol (3) in Fig. 5).

 - The receiving part 52-1 generates a baseband signal by despread a reception wave that has arrived from the terminal 82 in parallel with the above-mentioned reception wave and has been supplied via the antenna 71-1 and the antenna duplexer (indicated by
10 symbol (4) in Fig. 5) and generates a replacement baseband signal to replace the generated baseband signal by combining the baseband and the upstream transfer subject signal (indicated by symbol (5) in Fig. 5).

[0057]

 - Further, the receiving part 52-1 restores packets indicated by the replacement
15 baseband signal by performing decision decoding and transmission channel decoding on the replacement baseband signal and gives the (sequence of) packets to the router 74 (indicated by symbol (6) in Fig. 5).

 - The transmitting part 53-1 generates a transmission wave signal indicating the packets that have been given by the router 74-1 and are to be transmitted to the terminal 82
20 (indicated by symbol (7) in Fig. 5), and sends the generated transmission wave to the terminal 82 via the antenna duplexer 72-1, the antenna 71-1, and the downstream link of the above-mentioned particular radio channel (indicated by symbol (8) in Fig. 5).

[0058]

 - In generating the transmission wave, the transmitting part 53-1 passes, to the link
25 interface part 55-1, a baseband signal (hereinafter referred to as "downstream transfer

subject signal") that is modulated by the above-mentioned packets and is a subject of spreading that is performed in generating the transmission wave.

– The link interface part 55-1 forwards the downstream transfer subject signal to the radio base station 50-2 via the bypass channel (indicated by symbol (9) in Fig. 5).

5 [0059]

In the radio base station 50-2, the link interface part 55-2 and the transmitting part 53-2 performs the following processing in accordance with the logical value of the above-mentioned binary information:

– The link interface part 55-2 receives the downstream transfer subject signal via the
10 bypass signal and passes it to the transmitting part 53-2 (indicated by symbol (10) in Fig. 5).
[0060]

– The transmitting part 53-2 sends a transmission wave signal generated on the basis of the downstream transfer subject signal according to a direct sequence scheme to the terminal 82 via the antenna duplexer 72-2, the antenna 71-2, and the downstream link of the
15 above-mentioned joint radio channel (indicated by symbol (11) in Fig. 5).

That is, a reception wave sent from the terminal 82 to the radio base station 50-2 being not the particular radio base station is forwarded to the particular radio base station 50-1 as an upstream transfer subject signal. The upstream transfer subject signal thus forwarded is combined with a baseband signal that has been generated by despread a
20 reception wave that has arrived at the radio base station 50-1 in parallel with the above transmission wave, and a combined signal is subjected to demodulation, decision decoding, etc. Resulting (sequence of) packets are given to the router 74-1 as a subject of routing.
[0061]

The (sequence of) packets that have been given by the router 74-1 and are to be
25 transmitted to the terminal 82 are directly radio-transmitted from the particular radio base

station 50-1 to the terminal 82 and are also forwarded to the radio base station 50-2 being not the particular radio base station as a downstream transfer subject signal. The radio base station 50-2 radio-transmits the downstream transfer subject signal to the terminal 82 in parallel with the above (sequence of) packets.

5 [0062]

Therefore, according to this embodiment, a diversity handover can be attained in a stable manner though the IP is applied to the radio transmission sections, because an upstream transfer subject signal and a downstream transfer subject signal are forwarded in the baseband via the bypass link 51, and the radio base stations 50-1 and 50-2 cooperate
10 with each other in the above-described manner.

[0063]

The operation of the second embodiment of the invention will be described below with reference to Fig. 4.

This embodiment is characterized in the following processing procedure that is
15 followed by the base station controlling station 84.

Cooperating with the subordinate radio base stations (including the radio base stations 50-1 and 50-2), the base station controlling station 84 recognizes the particular radio base station for each terminal that performs a diversity handover and judges whether the particular radio base station is suitable for continuation of the diversity handover on the
20 basis of zone configurations of wireless zones formed by those radio base stations, channel allocation, frequency allocation, a modulation scheme, and a multiple access scheme.

[0064]

Further, when the judgment result is false, the base station controlling station 84 performs the following processing in cooperation with the particular radio base station and
25 other radio base stations among the radio base stations that should be involved in the

diversity handover concerned:

- Determines a new particular radio base station.

[0065]

- Regards the new particular radio base station as a transition destination (e.g.,
5 corresponds to the radio base station 70-2 in the conventional example) of a hard handover rather than a diversity handover.

- After completion of radio channel establishment for the transition destination, instructs the new particular radio base station to perform binding update by cooperating with the terminal 82 in the same manner as in the conventional example (indicated by symbols

10 (g)-(m) in Fig. 7).

[0066]

Therefore, this embodiment can prevent a state that continuance of a same radio base station being the particular radio base station from occurrence of a complete call at the terminal 82 to disappearance of the call causes the diversity handover not to properly comply
15 with the above-mentioned zone configurations, channel allocation, frequency allocation, modulation scheme, and multiple access scheme, which lowers the transmission quality and service quality, complicates the processings related to the channel control, and increases the load.

[0067]

20 This embodiment has not described specific criteria for the selection of a new particular radio base station. However, a new particular radio base station may be selected on any criteria in any of the following manners as long as desired service quality and transmission quality are secured under the configuration of a mobile communication system to which the invention is applied without undue cost increase:

25 [0068]

- Optimize the combination of wireless zones that should be used jointly during a diversity handover and reduce the number of joint wireless zones by preferentially selecting, according to the zone sizes and allocation and past results, a radio base station that forms a wireless zone the terminal 82 is likely to continue to visit.

- 5 - Deterioration in transmission quality or service quality can be avoided by preferentially selecting a radio base station that forms a wireless zone other than wireless zones that are small in traffic and hence are not prone to interference.

[0069]

In each of the above embodiments, an upstream transfer subject signal and a
10 downstream transfer subject signal are passed as signals in the baseband between the radio base stations 50-1 and 50-2 via a bypass channel (i.e., the bypass link 51). However, an upstream transfer subject signal and a downstream transfer subject signal may be signals in a desired intermediate frequency band or radio frequency band as long as they are generated in the physical layer and modulated by packets to be passed between the terminal 82 and the
15 router of a particular radio base station.

[0070]

Each of the above embodiments has not described the number of bypass channels that can be formed in parallel in the bypass link 51 specifically. However, the number of bypass channels may be any number as long as bypass channels are assigned properly to
20 calls and terminals as subjects of diversity handovers in such a manner as to conform to the topology and the transmission scheme of the bypass link 51.

[0071]

In each of the above embodiments, a bypass channel is assigned as appropriate to a call and a terminal as a subject of a diversity handover under the control of the base station
25 controlling station 84. However, for example, a bypass channel may be assigned under the

control of a particular radio base station that is determined uniquely during the course of a channel control or under cooperation between radio base stations that can be involved in a diversity handover as long as the bypass channel assignment is performed properly so as to conform to the topology and the transmission scheme of the bypass link 51.

5 [0072]

In each of the above embodiments, for example, the bypass link may be formed in advance as a set of bypass channels that are uniquely correlated with radio channels that can be assigned to complete calls in parallel by each radio base stations and the assignment of the radio channels and the assignment of the bypass channels may be unified with each other
10 as long as they conform to the topology and the transmission scheme of the bypass link.

[0073]

In each of the above embodiments, in a joint wireless zone, the terminal 82 is assigned a full-duplex joint radio channel that consists of the same upstream link as the upstream link of a particular radio channel and a downstream link that is different from the
15 downstream link of the particular radio channel. However, the joint radio channel may be any of the following radio channels:

[0074]

– Radio channel whose upstream and downstream links are different from the upstream and downstream links of a particular radio channel, respectively.

20 – Radio channel whose upstream and downstream links are common to the upstream and downstream links of a particular radio channel, respectively.

Each of the above embodiments has not disclosed specifically about a multiple access scheme, a modulation scheme, channel allocation, zone configurations, and frequency allocation that closely relate to the formation and assignment of such a radio channel.

25 [0075]

However, such a radio channel may be formed by using a plurality of desired multiple access schemes as long as a radio channel is recognized reliably under a channel control and the above-described diversity handover is realized.

In each of the above embodiments, the invention is applied to the diversity handover
5 that is performed in a duplex-operation mobile communication system.

[0076]

However, the application of the invention is not limited to such mobile communication systems and the invention can also be applied to simplex-operation and semi-duplex-operation mobile communication systems.

10 Each of the above embodiments has not disclosed specifically about a multiple access scheme that should be applied to the bypass link 51. However, any of CDMA (code division multiple access), TDMA (time division multiple access), FDMA (frequency division multiple access), and combinations of these multiple access schemes may be applied to the bypass link 51 as long as high transmission quality is attained without impairing combining
15 processing for realizing a diversity handover, and a bypass channel can be assigned reliably to a call or a terminal as a subject of the diversity handover.

[0077]

In each of the above embodiments, the router 74-C is provided in the radio base station 50-C. However, the router 74-C may be provided as an apparatus that is separate
20 from the radio base station 50-C or may be a router that is common to a plurality of radio base stations.

[0078]

In each of the above embodiments, the router 74-C may have function of routing in a private network between a base station controller and radio base stations formed and
25 operated by a communication company and/or a gateway interfacing with a public network.

[0079]

The invention is not limited to the above embodiments and various modifications may be made without departing from the spirit and scope of the invention. Any improvement may be made in part or all of the components.

- 5 Below, the invention disclosed above in each embodiment will be hierarchically and multilaterally sorted out and listed as an additional item.

[0080]

(Additional description 1) A radio base station apparatus including:

- 10 a receiving section 11 for receiving a signal from a terminal 10 via a radio channel assigned to the terminal 10;

an identifying section 12 for identifying a particular radio base station which is to maintain the radio channel between the radio base station apparatus and the terminal 10 during a process of a diversity handover for the terminal 10;

- 15 a network interface section 14 for delivering the signal to a network 13 when a local station is not the particular radio base station; and

an inter-office interface section 16 for delivering to the network 13 a composite wave of the signal and a signal that is forwarded from radio base stations 15-1 to 15-N forming a wireless zone adjacent to a wireless zone formed by the local station, when the local station is the particular radio base station, the forwarded signal having arrived at the
20 radio base station 15-1 to 15-N from the terminal 10 via the radio channel.

[0081]

(Additional description 2) A radio base station apparatus including:

- a receiving section 11 for receiving a signal from a terminal 10 via a radio channel assigned to the terminal 10;
- 25 an identifying section 12 for identifying a particular radio base station which is to

maintain the radio channel between the radio base station apparatus and the terminal 10 during a process of a diversity handover for the terminal 10;

a network interface section 14A for delivering the signal to a network 13 when a local station is not the particular radio base station; and

5 an inter-office interface section 16A for forwarding the signal to the particular radio base station among radio base stations 15-1 to 15-N that form wireless zones adjacent to a wireless zone formed by the local station when the local station is not the particular radio base station.

[0082]

10 (Additional description 3) A radio base station apparatus including:

a network interface section 22 for capturing a signal that is delivered from a network 21 in a physical layer of the network 21;

an identifying section 24 for identifying a particular radio base station which is to maintain a radio channel assigned to a terminal 23 as a receiving end of the signal during a
15 process of a diversity handover for the terminal 23;

a transmitting section 25 for transmitting the signal to the terminal 23 via the radio channel; and

an inter-office interface section 27 for forwarding the signal to radio base stations 26-1 to 26-N forming a wireless zone adjacent to a wireless zone formed by a local station,
20 when the local station is the particular radio base station.

[0083]

(Additional description 4) A radio base station apparatus including:

an inter-office interface section 27A for capturing a signal whose destination is a terminal 23 and that have been forwarded from radio base stations 26-1 to 26-N forming a
25 wireless zone adjacent to a wireless zone formed by a local station;

an identifying section 24A for identifying a particular radio base station which is to maintain a radio channel assigned to the terminal 23 during a process of a diversity handover for the terminal 23; and

a transmitting section 25A for transmitting the signal to the terminal 23 via the radio channel when the local station is not the particular radio base station.

[0084]

(Additional description 5) The radio base station apparatus according to Additional description 1, further including an inter-office link securing section 31 for securing a link according to a procedure of a channel control for assigning the radio channel to the terminal 10 or through cooperation with a base station controller 30 performing the channel control, the link being used for transfer of the signal between the radio base station apparatus and the radio base stations 15-1 to 15-N, wherein

the inter-office interface section 16 combines the received signal with a signal that is forwarded via the link secured by the inter-office link securing section 31.

[0085]

(Additional description 6) The radio base station apparatus according to Additional description 2, further including an inter-office link securing section 31 for securing a link according to a procedure of a channel control for assigning the radio channel to the terminal 10 or through cooperation with a base station controller 30 performing the channel control, the link being used for transfer of the signal between the radio base station apparatus and the particular radio base stations 15-1 to 15-N, wherein

the inter-office interface section 16A forwards the signal to the particular radio base station via the link secured by the inter-office link securing section 31.

[0086]

(Additional description 7) The radio base station apparatus according to Additional

description 3, further including an inter-office link securing section 31A for securing a link according to a procedure of a channel control for assigning the radio channel to the terminal 23 or through cooperation with a base station controller 30A performing the channel control, the link being used for transfer of the signal between the radio base station apparatus and the
5 radio base stations 26-1 to 26-N, wherein

the inter-office interface section 27 forwards the signal via the link secured by the inter-office link securing section 31A.

[0087]

(Additional description 8) The radio base station apparatus according to Additional
10 description 4, further including an inter-office link securing section 31A for securing a link according to a procedure of a channel control for assigning the radio channel to the terminal 23 or through cooperation with a base station controller 30A performing the channel control, the link being used for transfer of the signal between the radio base station apparatus and the radio base stations 26-1 to 26-N, wherein

15 the inter-office interface section 27A captures a signal that is forwarded via the link secured by the inter-office link securing section 31A.

[0088]

(Additional description 9) A base station controller including:

a channel controlling section 43 for performing a channel control over a terminal 40
20 in cooperation with radio base stations 42-1 to 42-P forming wireless zones 41-1 to 41-P where the terminal 40 can visit; and

a network interface section 45 for interfacing with a network 44 under the channel control, the network being a network in which a communication channel is to be formed between the base station controller and the terminal 40 via all or part of the radio base
25 stations 42-1 to 42-P, wherein

the channel controlling section 43, among the radio base stations 42-1 to 42-P, determines a particular radio base station according to the channel control and all or part of configuration of the wireless zones 41-1 to 41-P, channel allocation, and frequency allocation, the particular radio base station being to maintain a radio channel assigned to the terminal 40 during a process of a diversity handover for the terminal 40.

[0089]

(Additional description 10) The base station controller station according to Additional description 9, wherein the channel controlling section 43 performs the channel control such that a radio base station is to be the particular radio base station, the radio base station forming a wireless zone in which the diversity handover is done in a suitable manner for all or part of configuration of a wireless zone, channel allocation, and frequency allocation among the radio base stations 42-1 to 42-P.

[0090]

[Advantageous effect of the invention]

As described above, in the inventions according to claims 1 and 2, a diversity handover for an upstream radio transmission channel being formed between the radio base station apparatus and a terminal can be attained.

Also, in the inventions according to claims 3 and 4, a diversity handover for a downstream radio transmission channel being formed between the radio base station apparatus and a terminal can be attained.

Furthermore, in the inventions according to claim 5 and a more specific concept of claim 5, the base radio controller to be adaptable to various configurations of mobile communication systems is allowed, and the optimization of the form of a diversity handover is sought.

[0091]

Also, in the inventions according to claims 1, 2, 3, and 4, the adaptability to an increase or a decrease in the number of wireless zones used for diversity handover, which changes due to movement of a terminal, as well as the reduction of the number of links used for signal transfer between radio base stations will be made possible.

5 Therefore, in the mobile communication systems which adapt the aforementioned inventions, high transmission quality and service quality will be kept at low cost irrespective of what configuration the mobile communication system has and of what form and information a unit of transmission including transmission information and transmitted via a radio transmission channel has.

10 [Brief description of the Drawings]

Fig. 1 is a first principle block diagram of radio base station apparatus according to the present invention;

Fig. 2 is a second principle block diagram of radio base station apparatus according to the present invention;

15 Fig. 3 is a principle block diagram of base station controllers according to the present invention;

Fig. 4 shows first and second embodiments of the present invention;

Fig. 5 illustrates the operations of the first and second embodiments of the present invention;

20 Fig. 6 shows the configuration of an exemplary mobile communication system in which different IP addresses are assigned for respective wireless zones; and

Fig. 7 shows a conventional handover process.

[Explanation of referenced numerals]

10, 23, 40, 82 terminal

25 11 receiving section

	12, 24, 24A	identifying section
	13, 21, 44	network
	14, 22, 45	network interface section
	15, 26, 42, 50, 70	radio base station
5	16, 16A, 27, 27A	inter-office interface section
	25, 25A	transmitting section
	30, 30A, 84	base station controller
	31, 31A	inter-office link securing section
	41	wireless zone
10	43	channel controlling section
	51	bypass link
	52, 73	receiving part
	53, 75	transmitting part
	54, 76	controlling part
15	55	link interface part
	71	antenna
	72	antenna duplexer
	74	router
	81	wireless zone
20	83	communication link

[Document Name] Abstract

[Abstract]

[Problems to be solved]

5 The invention relates to a radio base station apparatus as well as a base station controller, and its object is to realize a diversity handover stably with high reliability without altering the basic configuration to a large extent.

[Means to solve the problems]

10 The radio base station apparatus has a receiving section for receiving a signal from a terminal via a radio channel assigned to the terminal, an identifying section identifying a particular radio base station that is to maintain a radio channel between the radio base station apparatus and a terminal during a process of diversity handover, a network interface section delivering a signal to a network if a local station is not the particular radio base station, and an inter-office interface section delivering to the network a composite wave of the signal and a signal having arrived and forwarded from the terminal via the radio channel at a radio base
15 station forming a wireless zone adjacent to a wireless zone formed by the local station if the local station is the particular radio base station.

[Selected Figure] Fig. 1